

WYSE 55 Set up for WYSE 50 Emulation

PC Style Keyboard

F1 DISP

Columns = 80
LineS = 24
Page = 1 x Lines

Cursor = STEADY LINE
Display = DARK
Autopage = OFF

Scrn Saver = ON
Char Cell = 10 x 15
80/132 = OFF

F2 GENRL

Personality = WYSE50Enhance = OFF
Scrl = JUMP
Rcv Cr = CR

AutoscrL = OFF
Monitor = OFF

Status Line = ON
Wrap EOL = OFF
Recognize Del = OFF

F3 KEYBD

Keyclick = OFF
Keylock = CAPS
Language = US

Repeat = ON
Margin Bell = OFF
Corner Key = FUNCT

Key Code = ASCII
Bell Volume = 3

F4 COMM

Comm = FDX
Mdm Rc Hsk = XON-
Aux Rc Hsk = NONE

Xmt Line = NONE
Modem Rc Hsk Level = 192
Send Ack = OFF

Anwer Back Mode = OFF
Mdm Xmt Hsk = XON-XOFF/XPCXOFF
Aux Xmt Hsk = NONE

F5 PORTS

Mdm Baud Rate = 19200* Mdm Data/Parity = 8/NONE* Mdm Stop Bits = 1*
Aux Baud Rate = 9600 Aux Data/Parity = 8/NONE Aux Stop Bits = 1
Host Port = Modem Port

*** Must be set to port configuration**

F6 MISC

Wprt Intensity = DIM
Blk End = US/CR
Printer Attached = ON
Nulls Suppress = ON

Wprt Rev = OFF
Attribute = PAGE

Wprt Undrln = OFF
Multiple Page = OFF
Rest/Act Times = NONE

F7 ANSI 1 Not applicable for WYSE50 Emulation.

F8 ANSI 2 Not applicable for WYSE50 Emulation.

F9 TABS None Set

F10 ANSBK No

F11 FKEYS

Default