

## WYSE 55 Set up for WYSE 50 Emulation

### PC Style Keyboard

#### **F1 DISP**

Columns = 80  
LineS = 24  
Page = 1 x Lines

Cursor = STEADY LINE  
Display = DARK  
Autopage = OFF

Scrn Saver = ON  
Char Cell = 10 x 15  
80/132 = OFF

#### **F2 GENRL**

Personality = WYSE50Enhance = OFF  
Scrl = JUMP  
Rcv Cr = CR

AutoscrL = OFF  
Monitor = OFF

Status Line = ON  
Wrap EOL = OFF  
Recognize Del = OFF

#### **F3 KEYBD**

Keyclick = OFF  
Keylock = CAPS  
Language = US

Repeat = ON  
Margin Bell = OFF  
Corner Key = FUNCT

Key Code = ASCII  
Bell Volume = 3

#### **F4 COMM**

Comm = FDX  
Mdm Rc Hsk = XON-  
Aux Rc Hsk = NONE

Xmt Line = NONE  
Modem Rc Hsk Level = 192  
Send Ack = OFF

Anwer Back Mode = OFF  
Mdm Xmt Hsk = XON-XOFF/XPCXOFF  
Aux Xmt Hsk = NONE

#### **F5 PORTS**

Mdm Baud Rate = 19200\*    Mdm Data/Parity = 8/NONE\*    Mdm Stop Bits = 1\*  
Aux Baud Rate = 9600    Aux Data/Parity = 8/NONE    Aux Stop Bits = 1  
Host Port = Modem Port

**\* Must be set to port configuration**

#### **F6 MISC**

Wprt Intensity = DIM  
Blk End = US/CR  
Printer Attached = ON

Wprt Rev = OFF  
Attribute = PAGE  
Nulls Suppress = ON

Wprt Undrln = OFF  
Multiple Page = OFF  
Rest/Act Times = NONE

#### **F7 ANSI 1**

Not applicable for WYSE50 Emulation.

#### **F8 ANSI 2**

Not applicable for WYSE50 Emulation.

#### **F9 TABS**

None Set

#### **F10 ANSBK**

No

**F11 FKEYS**

Default